## **NP-Series - Valve Regulated Lead Acid Battery NP7-12L**

SPECIFICATIONS			
Nominal voltage	12	V	
20-hr rate Capacity to 1.75VPC at 20°C	7	Ah	
10-hr rate Capacity to 1.75VPC at 20°C	6.4	Ah	
DIMENSIONS	0.4	70	
	151 (+1)		
Length Width	151 (±1) 65 (±1)	mm	
Height	00 (±1)	mm mm	
(height over terminals)	97.5 (±2)	mm	
Mass (typical)	2.65	kg	
TERMINAL TYPE	2.00	itig	
FASTON (Quickfit / release)	6.35	mm	
OPERATING TEMPERATURE RANGE	0.00		
	-20°C to		
Storage	-20°C to -15°C to		
Charge Discharge	-15°C to -20°C to		
STORAGE	-20 C IC	0 +60 C	
Capacity loss per month at 20°C (approx)	3	%	
CASE MATERIAL	3	/0	
Standard Option	ABS (UL		
		,	
Flame retardant option (FR)	ABS (UI	_94.V0)	
CHARGE VOLTAGE	13.65 (±1%)	V	
Float charge voltage at 20°C	2.275 (±1%)	V/cell	
Float Charge voltage temperature correction factor (for variations from the standard 20°C)	-3	mV/cell/°C	
Cyclic (or Boost) charge at 20°C	14.5 (±3%) 2.42 (±3%)	V V/cell	
Cyclic Charge voltage temperature correction factor (for variations from the standard 20°C)	-4	mV/cell/°C	
CHARGE CURRENT			
Float charge current limit	No limit	А	
Cyclic (or Boost) charge current limit	1.75	Α	
MAXIMUM DISCHARGE CURRENT			
1 second	210	А	
1 minute	70	А	
SHORT-CIRCUIT CURRENT & INTERNAL RESISTANCE			
(according to EN IEC 60896-21)			
Internal resistance	N/A	mû	
Short-Circuit current	N/A	А	
IMPEDANCE			
Measured at 1 kHz	23	mΩ	
PERFORMANCE & CHARACTERISTICS			
Refer to the technical manual	NP		
DESIGN LIFE			
EUROBAT Classification: Standard Commercial	3 to 5	years	
Yuasa design life @ 20°C	up to 5	years	
SAFETY	0p 10 0	,00.0	
Installation			



LA۱	YOUT		
	$\oplus$		
	Θ		

## **3RD PARTY CERTIFICATIONS**

ISO 9001 - Quality Management Systems ISO 14001 - Environmental Management Systems EN 18001 - OHSAS Management Systems UNDERWRITERS LABORATORIES Inc. VdS (Germany) - VdS No: G189049

## **STANDARDS**

IEC61056









# **Data Sheet**

## Installation

Can be installed and operated in any orientation except permanently inverted

#### Handles

Batteries must not be suspended by their handles (where fitted)

## Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

#### **Gas Release**

VRLA Batteries release hydrogen gas which can form explosive mixtures in air. Do not place inside a sealed container

### Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations

ALL DATA IS SUBJECT TO CHANGE WITHOUT NOTICE Issue No.: V.1 / Issue Date: July 2010



YUASA BATTERY SALES UK LTD. Unit 22 Rassau Industrial Estate Ebbw Vale, Gwent NP23 5SD UK

	NP	
www.yuasaeurope.com	NP	